



**KINO FLO**  
Lighting Systems

# DIVA LITE<sup>®</sup> LED



# Divalite® 21/31/41



**D**iva-Lite® LED has four menu options, one white, two colors and **FX**. In the white menu, the Kelvin range is from 2700K to 6500K with **Dimming**, **Kelvin** and **Green/Magenta** control channels. In the color menu, Kelvin range is from 2500K to 9900K, with three additional channels, **Gel**, **Hue Angle** and **Saturation**. The Gel channel includes Kino Flo presets and over 100 well-known lighting gels. The second color menu provides individual **RGB** (red, green, blue) control. The **FX** (Effects) menu has custom presets like Candle, Fire, TV, Police, Lightning, Paparazzi, Pulse and Scroll.

The Diva-Lite LED comes with standard DMX, wireless DMX (Lumen Radio®), universal voltage input 100-240VAC and 24VDC. SnapBag Softbox and SnapBag accessories are also available.

**Features include:**

- Tunable Kelvin 2500K-9900K
- Dimming without color shift
- Green/Magenta control
- Kino Flo presets and Gels
- Dial in any color through Hue Angle and Saturation control
- RGB control
- FX (Effects) control
- Universal input 100VAC-240VAC and 24VDC
- Manual and DMX dimming w/ Auto Terminate
- DMX wireless (Lumen Radio)
- Flicker-free, quiet operation
- Honeycomb Louver, Center Mount and Yoke Mount

▼ Diva-Lite 21 LED DMX Center



**DIV-L21XCU**  
Diva-Lite 21 LED DMX  
Center Mount, Univ



**LVR-SL290-P**  
Diva-Lite 21  
Louver/HP, 90°  
(Included)



**MTP-LBC**  
Kino 41 Lollipop w/  
Baby Receiver Curve  
(16mm) (Included)

▼ Diva-Lite 21 LED DMX Yoke



**DIV-L21XYU**  
Diva-Lite 21 LED DMX  
Yoke Mount, Univ



**LVR-SL290-P**  
Diva-Lite 21  
Louver/HP, 90°  
(Included)

▼ Diva-Lite 31 LED DMX Center



**DIV-L31XCU**  
Diva-Lite 31 LED DMX  
Center Mount, Univ



**LVR-SL390-P**  
Diva-Lite 31  
Louver/HP, 90°  
(Included)



**MTP-LBC**  
Kino 41 Lollipop w/  
Baby Receiver Curve  
(16mm) (Included)

▼ Diva-Lite 31 LED DMX Yoke



**DIV-L31XYU**  
Diva-Lite 31 LED DMX  
Yoke Mount, Univ



**LVR-SL390-P**  
Diva-Lite 31  
Louver/HP, 90°  
(Included)



# Divalite® 21/31/41

## ▼ Photometrics

### Divalite 21

FC	508	154	70	40	26	18	14	11	9	7
Feet	2	4	6	8	10	12	14	16	18	20
LUX	7113	2409	1121	634	412	288	212	164	131	106
Meters	0.5	1	1.5	2	2.5	3	3.5	4	4.5	5

### Divalite 31

FC	510	161	75	43	28	20	15	11	9	8
Feet	2	4	6	8	10	12	14	16	18	20
LUX	7270	2470	1190	683	445	312	233	181	146	117
Meters	0.5	1	1.5	2	2.5	3	3.5	4	4.5	5

### Divalite 41

FC	481	161	77	45	29	21	16	12	10	8
Feet	2	4	6	8	10	12	14	16	18	20
LUX	6840	2450	1210	712	462	325	242	189	153	123
Meters	0.5	1	1.5	2	2.5	3	3.5	4	4.5	5

## ▼ Fixture Specifications

Fixture	Input Voltage VAC	Amps VAC	Input Voltage VDC	Amps 24VDC	Kelvin Range	Dimming Range	Dimensions	Weight
Divalite 21 Center	100-240VAC, 50/60Hz, 150W	1.25A, 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	23.5 x 4.5 x 11.5" (60 x 11.5 x 29cm)	12 lb (5.5kg)
Divalite 21 Yoke	100-240VAC, 50/60Hz, 150W	1.25A, 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	28.5 x 4.5 x 14.5" (72.5 x 11.5 x 37cm)	13 lb (6kg)
Divalite 31 Center	100-240VAC, 50/60Hz, 150W	1.25A, 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	37.5 x 4.5 x 9.5" (95 x 11.5 x 24cm)	14 lb (6.5kg)
Divalite 31 Yoke	100-240VAC, 50/60Hz, 150W	1.25A, 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	42 x 4.5 x 12" (107 x 11.5 x 30.5cm)	14.5 lb (6.5kg)
Divalite 41 Center	100-240VAC, 50/60Hz, 150W	1.25A, 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	49.5 x 4.5 x 7.5" (126 x 11.5 x 19cm)	15 lb (7kg)
Divalite 41 Yoke	100-240VAC, 50/60Hz, 150W	1.25A, 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	56 x 4.5 x 10" (142 x 11.5 x 25.5cm)	15.5 lb (7kg)

## ▼ Divalite 41 LED DMX Center



**DIV-L41XCU**  
Divalite 41 LED DMX Center Mount, Univ



**LVR-SL490-P**  
Divalite 41 Louver/HP, 90° (Included)



**MTP-LBC**  
Kino 41 Lollipop w/ Baby Receiver Curve (16mm) (Included)

## ▼ Divalite 41 LED DMX Yoke



**DIV-L41XYU**  
Divalite 41 LED DMX Yoke Mount, Univ



**LVR-SL490-P**  
Divalite 41 Louver/HP, 90° (Included)

## ▼ Details



Divalite 41



## ▼ Divalite LED DMX Kits



**KIT-DL21XU**  
Divalite 21 LED DMX Center Kit w/ Travel Case, Univ

Contents	Dimensions	Weight
1 Divalite 21 LED DMX Center, Univ	28.5 x 8.5 x 16"	22.5 lb
1 Travel Case	(72.5 x 22 x 41cm)	(10kg)



**KIT-DL31XU**  
Divalite 31 LED DMX Center Kit w/ Travel Case, Univ

Contents	Dimensions	Weight
1 Divalite 31 LED DMX Center, Univ	45.5 x 9 x 16.5"	33.5 lb
1 Travel Case	(116 x 23 x 42cm)	(15kg)

# Diva-Lite® 21/31/41

## ▼ Diva-Lite LED DMX Accessories/Cases



**SYS-BK12**  
Block/KF21 Single Battery System,  
140Whr, 28.8V (2 x Battery)



**MTP-B41F**  
Kino Offset  
w/ Baby Receiver (16mm)



**STD-M30**  
Medium Duty, 30"  
**STD-M36**  
Medium Duty, 36"



**BRD-D21**  
Diva-Lite 21 Barndoors (Set of 2)  
**BRD-D31**  
Diva-Lite 31 Barndoors (Set of 2)  
**BRD-D41**  
Diva-Lite 41 Barndoors (Set of 2)



**MTP-LBC**  
Kino 41 Lollipop  
w/ Baby Receiver Curve (16mm)



**STD-D1**  
Reverse Stand



**LVR-SL260-P**  
Diva-Lite 21 Louver/HP, 60°  
**LVR-SL360-P**  
Diva-Lite 31 Louver/HP, 60°  
**LVR-SL460-P**  
Diva-Lite 41 Louver/HP, 60°



**MTP-LBS**  
Kino 41 Lollipop  
w/ Baby Receiver Short (16mm)



**KAS-DL21-C**  
Diva-Lite 21 Travel Case



**DFS-FS21-S**  
Diva-Lite 21 SnapBag w/ 2 x Diffusion  
**DFS-FS31-S**  
Diva-Lite 31 SnapBag w/ 2 x Diffusion  
**DFS-FS41-S**  
Diva-Lite 41 SnapBag w/ 2 x Diffusion



**MTP-I40**  
Baby Receiver Assembly  
for Yoke (16mm)



**KAS-DL31-C**  
Diva-Lite 31 Travel Case



**LVR-FS240-S**  
Diva-Lite 21 SnapGrid, 40°  
**LVR-FS340-S**  
Diva-Lite 31 SnapGrid, 40°  
**LVR-FS440-S**  
Diva-Lite 41 SnapGrid, 40°



**MTP-I80**  
Junior Pin Assembly  
for Yoke (28mm)



**7010055**  
Diva-Lite 21 Yoke Assembly  
**7010057**  
Diva-Lite 31 Yoke Assembly  
**7010059**  
Diva-Lite 41 Yoke Assembly



**Kino Flo Lighting Systems**  
2840 North Hollywood Way  
Burbank, CA 91505

+1 818 767 6528 voice +1 818 767 7517 fax

[www.kinoflo.com](http://www.kinoflo.com)  
©Kino Flo Diva-Lite 21/31/41  
No. 3110116 Rev B